



quikö:

QK-R02

2ch radio receiver

Power supply / ALIM.

12/24vAC-DC

Abortion / ASSORB.

15mA in stand-by

Frequency / FREQ.

433,92Mhz

Storable codes / MEM.

400

N° of channels / CAN.

2

Contact capacity / REL.

1 A/24V

Operating temperature

-20+70°C

Dimensions / DIM.

6x3xH2,5cm

V04

www.quikitaly.com
MADE IN ITALY

JP4=ON STEP-BY-STEP CH1
JP4=OFF MOMENTARY CH1
JP1=ON STEP-BY-STEP CH4
JP1=OFF MOMENTARY CH4

INSTRUCTION: On the receiver press P1, 1 time for CH1, 2 times for the CH2 (the led flashes twice). LED lights up. Within 5 seconds press the Key of the remote control to be memorised. The LED switches OFF. The Remote Key is memorised.

MEMORY RESET: In case of mistake or if all the codes need to be deleted, press P1 (the led lights up) and hold it down until the LED switches OFF. After releasing P1, the LED flashes once (indicating that the memory is empty).

ISTRUZIONI: Sulla ricevente premere il tasto P1, una volta per CH1 e due volte per CH2 (il led fa due lampeggi). Si accende il led. Premere il tasto del telecomando che si vuol fare apprendere, il led si spegne. Apprendimento avvenuto.

CANCELLAZIONE DELLA MEMORIA per cancellare tutti i codici in memoria (sia ch1 che ch2) premere il tasto P1 e tenerlo premuto fino a quando si spegne il led. Una volta rilasciato P1 il led si riaccende e si rispegne per indicare memoria vuota.

CE CONFORMITY DECLARATION

the manufacturer declares that the QK-R02 comply with the following norms

EN301489-3(2000)CLASSE1 EN300 220-1 V2.1.1 EN 60 950 MOD.A1 (1993)-A3(1995)-A4(1997)

And that the above mentioned product has been tested in a typical installation and fulfil the essential requirements of the laws:: 99/5/CEE