

Model No.
ST-36

Stark Emergency SOS box



Product Overview:

Emergency button detector, once the emergency incident occurs, the detector will be triggered to transmit the signal to the alarm system. This product is suitable for all the places where the security protection is needed, such as residential areas, companies, shopping malls, hospitals, banks, guard post etc.

Features:

- Double alarm types, button type and pull type.
- Compact appearance, can hang it up.
- Anti-false alarm design.
- Zero standby power consumption.
- Low-battery detection.
- MCU coding, compatible with 2262/ 1527.
- Anti RFI (20V/m-1GHz).
- SMT process.

Technical Parameters

Working voltage	3V (1*CR2032 button cell)
Alarm Current	≤25mA
Standby Current	0 μA
Emission frequency	433.92MHz
Operating temperature	10°C ~ +50°C
Wireless transmitting range	50m - 100m (open area)
Magnet dimension (L*W*H)	38*58*15mm
Humidity	≤80%
Alarm Type	Button type and pull type